

Manufacturer	Equipment Type	Telephone/Console	Headset Key Prog.?	Corded Solution(s)	M22/12 Set-up*	Cordless Solution(s)	Comments
3COM NBX	2102/3101/3102			M22 & H-Top or P-Top	S5	Y: S1, TB.	P-Top does not work on 3102, HL10 extender may be needed for lifter.
				M15D & H-Top	SA		
ACRO		ADP-2000		M-Top			
ALCATEL	1200 Series	1200C		M22 with H-Top	S6,T2	CS Series, 510 Syst.	
	4200 and 4400 Series	4001, 4003, 4011		M22 with H-Top or P-Top	S5,T2	Y: S1, TB, R3	
	4200E, 4400			M12E, A20		CS Series, 510 Syst.	Program phone for headset
		4012, 4023, 4034, 4040	System Administrator	M22 with H-Top or P-Top	S5,T2	Y: S1, TB, R3	
	4300 Series	Console	Automatic	M22 with H-Top or P-Top		CS Series, 510 Syst.	
		Digital Handset 4321, 4304 & Others	Yes	M22 with H-Top or P-Top		Y: S1, R3	4321 and 4304 Headset compatible if operating in ACD groups
	5200 Series	Console		M22 with H-Top	S5,T2	CS Series, 510 Syst.	
		Digital Handset 4019 TDM / 4029 / 4039		P-Top			
	9000 Series	4074B		H-Top & QD-3.5mm			
	DECT Handsets	4074H		----		----	Not Compatible
		4074H		CHS142N-4AR/A			Alcatel specific version
	Digital Telephone	Cordless 100 / 200		M-Top			
		4035		Vista Cable & H-Top or P-Top		Y: S1, TB, R3	
	Hotel Sets	2315 / 2325					
	IP Touch	4018		H-Top & QD-3.5mm		Y: S1, TB, R3	
	IP Touch	4028 / 4038 / 4068		H-Top & QD-3.5mm		Y: S1, TB, R3	AP-2 EHS Module available, to eliminate mechanical lifter
	PCX Office	4400					
	PCX Office	Remote 4400					
	Pimphony Softphone	Pimphony IP Softphone		H-Top & DA-60		CS60-USB	
	Single Line Tel.	1000, 1050, 500, 550, 2000, 2730		----		----	Not Compatible
	2111, 2112		M22 with H-Top		CS Series, 510 Syst.		
	5101		M12E, A20		CS Series, 510 Syst.	5101 Modification Required	
SLT Telephones	2410, 2412		M12E, A20		CS Series, 510 Syst.		
Starswitch	Console	Automatic	P10 with H-Top				
	Digital Handset	Yes	M22 with H-Top		CS Series, 510 Syst.		
	Reflexes	Automatic	P Cable with H-Top		CS Series, 510 Syst.		
	4047 IP		P-Top		CS Series, 510 Syst.		
ARIA (Also refer LG Aria)	System Telephones	16, 28, 34, 100, 148, 162, 186.		M12E, A20		CS Series, 510 Syst.	Program : [TRAN/PNG] 5 7 enables; [TRAN/PNG] 5 7 disables; [MON] is used to answer and release calls.
	System Telephones	20, 50, 300, 600		M12E, A20		CS Series, 510 Syst.	Program for headset button
	Select Keysets	34E		P-Top		CS Series, 510 Syst.	Program : [TRAN/PNG] 5 7 enables; [TRAN/PNG] 5 7 disables; [MON] is used to answer and release calls.
	LDP-700	VoIP series phones		2.5mm Ad. & H-Top			
ARISTEL	AV Series	DKP 30 / 31 / 33 (16-button models) and DKP10 (25-button models).	Yes	P-Top & Biway		CS Series, 510 Syst.	B-10 Setting "4 A" Headset Program "Speaker #53#"
		DKP 50 / 51 / 53 / 53B (20-button models)	Yes	P-Top & Biway		CS Series, 510 Syst.	As Above. Aristel Firmware late 2006 adds full wireless connectivity, to CS60/70/351/361 and 510 System
	DV Series			P-Top & QD-2.5mm or Top & Biway	P-		Will Auto detect headset when connecting via the 2.5mm headset socket. Manual programming required if using the Biway with P-Top. Headset Program "Speaker #56"
ASPECT		Teleset 2	Yes	A10-21 & H-Top or M22 with H-Top		Y: S1, TD, R3	
		Winset	Yes	A10-28 & H-Top or M22 with H-Top		Y: S1, TD, R4	



Headset Solutions

Compatibility Guide - May 2007

Manufacturer	Equipment Type	Telephone/Console	Headset Key Prog.?	Corded Solution(s)	M22/12 Set-up*	Cordless Solution(s)	Comments	
AT&T Definity (refer Avaya, previously Lucent)	Digital 84 Series	8403,8410,8434,8434DX		M22 with H-Top		CS Series, 510 Syst.	M12E Not compatible	
	Callmaster			M22 with H-Top	S1	CS Series, 510 Syst.	M12 + 18709-01(KH726). M12E Not compatible	
AUDIOLINE		502, 503, 505, 506.		M22 with H-Top		CS Series, 510 Syst.		
		AJB3 / AUB4		M12 with H-Top		Y: S1, T, R3	Cannot be programmed	
		Casino		T100 & H142N				
		Phone Easy		M22 with H-Top		CS Series, 510 Syst.		
		Sensor 500				Y: S1, T, R3	26585.01 P-cable	
		Tel-6, Tel-7, Tel-8, Tel-17, Tel-18, Tel-25, Tel-51.		M22 with H-Top		CS Series, 510 Syst.	Cannot be programmed	
	7000 Series	7004, 7008, 7016, 7024, 7024LD						
Cordless	CP60, CP70, CP70+1, FF895		Mobile Headset					
AURORA								
	ACC3100	103 Mini-COM		M22 with H-Top		CS Series, 510 Syst.		
AYAYA (Previously LUCENT, Previously AT&T)	2400 Series Digital	2402, 2410, 2420 - Series 2		H-Top & HIC-1 Cable		Y: S2, TB, R3	2420 supports AHW-65 & ABT-35 Wireless	
	2500 Series Analogue	MMGN / YMGP						
	4400 Series			M22 & H-Top or H-Top & HIC-1 Cable		CS Series, 510 Syst.		
	4600 IP Telephones	4606, 4612, 4624 -SERIES 2.1			H-Top & HIP-1 Cable		CS Series, 510 Syst.	Requires Bi-Way switch to use handset on phone models without a headset port. IP4600 - use an adapter cable (62367-01) for connecting to a CA40. SupraPlus performs best.
		4602, 4620, 4622 -SERIES 2.2			H-Top & HIC-1 Cable		Y: S2, TC, R2	SupraPlus recommended, not H141, H141N. 4620 & 4622 support AHW-65 & ABT-35 Wireless.
	4020							
	5400 Series	5402 / 5410 / 5420		H-Top & HIC-1 Cable		Y: S2, TC, R2	5410 & 5420 support AHW-65 & ABT-35 Wireless.	
	5600 IP Series	5601 / 5602 / 5608 / 5610 / 5620		H-Top & HIC-1 Cable		Y: S2, TC, R2	5610 supports AHW-65 & ABT-35 Wireless.	
	6200 Analogue	6211 / 6219 / 6221						
	Definity ProLogix (6400 Series)	6402, 6402D, 6408D			Contact Plantronics		CS Series, 510 Syst.	Avaya M12LU with H-Top
		6416D+, 6424D+, 302D Attendant Cons.			Contact Plantronics		Y: S2, TC, R2	6424 D+M supports AHW-65 & ABT-35 Wireless
	6400 Series Definity ProLogix	6408D+ / 6416D+ / 6424D+			M12LU & H-Top or HIC-1 Cable	H-Top &	CS Series, 510 Syst.	HIC-1 solution requires BiWay switch to use handset on phone models without a headset port
	Definity ECS (7400 Series)	7401, 7401+, 7406, 7406+, 7407, 7407+, 7410, 7410+, 7434, 7444, 7444+		Yes	M22 & H-Top, or P-Top	S2,T3	CS Series, 510 Syst.	
		8403, 8410B, 8410D, 8434, 8434DX		Yes	M22 & H-Top, or P-Top	S5,T1	CS60: S2, TC, R2	Reverse handset wall mounting hook to stop hook-switch from being depressed.
	9031, 9200			Yes	P-Top	S5,T1	CS Series, 510 Syst.	
	ACD Consoles				M-Top			
		Call Master (603), Plus, Att' Console (302)			P10 with H-Top			
		Call Master V			H-Top & Vista Cable, or P-Cable		Y: S4, TB, R2	Cable required depends on telephone wiring
		Call Master VI			H-Top on P-Cable		Y: S4, TB, R3	P cable supplied with new phones
	AT&T	Digital Handsets	Yes		M22 with H-Top	S5,T2		
DCS, DCS Compact				H-Top & P Cable (recommended), or P Top, or H12 & H Top	S5,T2	CS Series, 510 Syst.	setting 5 (Batteries). P-Top will replace handset.	
Index	LCD 24B, STD 24B, STD 12B & 6B Basic	Yes		H-Top & P Cable (recommended), or P Top, or H12 & H Top		CS Series, 510 Syst.	setting 5 (Batteries). P-Top will replace handset.	
Turrent 20CC				H-Top on P-Cable		CS Series, 510 Syst.		
Voiceworks ACS/CS	910, 930, 930a, 960a			H-Top on P-Cable		CS Series, 510 Syst.		



Manufacturer	Equipment Type	Telephone/Console	Headset Key Prog.?	Corded Solution(s)	M22/12 Set-up*	Cordless Solution(s)	Comments	
British Telecom (BT)	Dealing room sys.			M22 with H-Top	S5,T2	Y: S1, TD, R	May req. 6x4 modular stub and socket cables	
		CT100 / CT250		M22 with H-Top		CS Series, 510 Syst.	Alternate: M12E, A20	
CISCO SYSTEMS		7902 / 7905 / 7905G		M22 & H-Top		Y: S1, T, R3		
		7910/7912		M22 & H-Top or P-Top & Biway		Y: S1, T, R3	B10 Switchbox is required for latest wiring of 7910 / 7912 Settings: either "4 A" or "4 B" depending on manufacture date	
		7940 / 7960		H-Top & Vista Cable		Y: S1, T, R3	Built in Headset Connection	
		7970/7971		H-Top & Vista Cable		Y: S1, T, R3	Built in Headset Connection	
	Cordless IP Phones	7920		2.5 mm to QD, & H-Top				
Softphones	Softphone V1.3			H-Top on DA60		CS60 / 510 USB	Full Hookswitch Control on V1.3 and above	
	Communicator			H-Top on DA60		CS60 / 510 USB	Full Integrated Hookswitch Control.	
COMDIAL	Scout			M-Top				
COMMANDER	Commander AN	616	Kit Req.	M22 & H-Top	S5T2	CS Series, 510 Syst.	Handset volume down; use M22 volume	
	Commander BN	308/512/824/1236/2464	Kit Req.	M22 & H-Top	S5T2	CS Series, 510 Syst.	Handset volume down; use M22 volume For S12 use setting S3T2	
	BCM / 50 (Nortel)	T7208, T3716E, T7000, T7100		P-Top	T 5	Y: S1, TC, R3	Volume may be low with P-Top. M22 & H-Top ( Please Refer Nortel BCM Section).	
	BCM / 50 IP (Nortel)	i2001			P-Top		CS Series, 510 Syst.	Alternate - M22 & H-Top
		i2002, i2004, i2007			Refer Nortel Section		CS Series, 510 Syst.	Refer Nortel Section
		1140E/1120E			Refer Nortel Section		CS Series/510Syst	510 Hookswitch with BT inbuilt in 1140E, FW Rel Rel C22.
	IP Softphone 2050(2050)			DA45 & H-Top		CS60USB /510USB		
	Connect	Standard & Executive		P-Top		CS Series, 510 Syst.	Alternate - M22 & H-Top	
	Commander D	32 / 72 / 128	Yes	M12E & H-Top or H-Top & Vista Cable	S3T2	CS Series, 510 Syst.	Program: [SPKR] 626 [SPKR]	
	Commander E	105 / 105+ / 208 / 208+ / 308 / 616	No	M12E & H-Top or H-Top & Vista Cable	S3T2	CS Series, 510 Syst.		
	Commander F	120	Yes	M22 & H-Top		CS Series, 510 Syst.		
	Commander HX	308 / 616 / 1224	User	M22 & H-Top	S5T2	CS Series, 510 Syst.	Handset volume down; use M22 volume Program: # 1 5 1 #	
	Commander I	408 / 408+	Yes	M22 & H-Top or H-top & P Cable	S5T2	CS Series, 510 Syst.		
	Commander Meridian/CS1000	2050, 3901, 3902, 3903, 3904, 3905, 1140E, 1120E		Refer Nortel Section		CS Series, 510 Syst.	Refer Nortel Section	
	Commander N	308 / 616 / 1236 / 2260	No	M22 & H51	S1T2	CS Series, 510 Syst.	Headset adaptor kits no longer available	
	Commander NT (40 / 40C / 132)	Economy	No	M22 & H-Top or P-Top	S5T2	CS Series, 510 Syst.	No headset port; replace headset with P-Top	
		Standard / Advantage / Principle	Yes	M22 & H-Top or P-Top	S5T2	CS Series, 510 Syst.	Dedicated headset port. full hands-free to get headset key Program for	
	Commander S	206 / 408 / 824		M22 & H-Top	S5T2	CS Series, 510 Syst.	Handset volume down; use M12 volume	
		207 / 416 / 620	N/A	Not Compatible		Not Compatible	Handsets are hardwired	
	Commander T	T105	N/A	Not Compatible		Not Compatible	Handsets are hardwired	
		106 / 210	Yes	M22 & H-Top	S1T2	CS Series, 510 Syst.	Handset volume down; use M12 volume	
	Commander Elite	Standard / Exec / Premier	Yes	P-Top		CS Series, 510 Syst.	Dedicated headset port	
	Commander Hi Path 3000/4000	Optipoint 130 - Softphone			DA45 & H-Top	N/A	CS60USB /510USB	
Optipoint 410 Entry, Economy, Economy Plus & Standard.				M22 & H-Top		CS Series, 510 Syst.		
Optipoint 410 Advanced				P-Top		CS Series, 510 Syst.		
Optipoint 420 Entry, Economy, Economy Plus & Standard.				M22 & H-Top		CS Series, 510 Syst.		
Optipoint 420 Advance				P-Top		CS Series, 510 Syst.		
Optipoint 500 Entry, Economy, Economy Plus & Standard.				M22 & H-Top		CS Series, 510 Syst.		
Optipoint 500 Advance				P-Top		CS Series, 510 Syst.		
OptiPoint 600 Office Advanced				M12 & H-Top	S5,T2	Y: S1, TB, R3		



Headset Solutions

Compatibility Guide - May 2007

Manufacturer	Equipment Type	Telephone/Console	Headset Key Prog.?	Corded Solution(s)	M22/12 Set-up*	Cordless Solution(s)	Comments
<b>Concerto Software</b>							
	Davox	Handsets		M22 & H-Top		Y: S1, T, R3	
<b>CONNECT (Compact)</b>							
	Standard / Executive			P-Cable & H-Top	S1	CS Series, 510 Syst.	
<b>DATAPoint</b>							
	Infoswitch (ACD)	Handsets		H-Top & Vista Cable	S5	Y: S1, T, R3	
<b>DBA</b>							
	SmartTalk 308	Handsets		M22 with H-Top	S5	Y: S1, T, R3	
<b>DeTeWe</b>							
	Cordless			Refer Plantronics			DeTeWe Specific M-Top available.
	Deskphone	OpenComm		Refer Plantronics		CS Series, 510 Syst.	DeTeWe EHS module available.
<b>DORO</b>							
	Afti	20 / 30 / 40		M22 & H-Top			
	Congress	100 / 200 / 305		H-Top & P Cable	S5	Y: S1, T, A, R3	Also T100 & H142N Headsets. Dedicated port.
	CRT	10		M22 & H-Top		CS Series, 510 Syst.	
	DECT	5035, 5045, 8075, 8085, CP60, CP702, CP70, CP70+1, FF895		M-Top			
<b>ELITE</b>							
	Std/Exec/Premier	Handsets		M22 & H-Top		CS Series, 510 Syst.	
<b>ERICSSON</b>							
	ASB30, ASB100, ASB900, BCS90	Console	Standard	M22 with H-Top	S1T2	CS Series, 510 Syst.	Termination - Lemo Plug
	ASB900	Console	Standard	M22 with H-Top		CS Series, 510 Syst.	Termination - Lemo Plug
	BCS150 / 250	2751, 2752, 2753, 2755	Yes	M12E, A20		CS Series, 510 Syst.	
		Console 2754	Standard	M22 with H-Top		CS Series, 510 Syst.	Termination - Lemo Plug
	BP24 / 40	System Phones, Console		M22 with H-Top		CS Series, 510 Syst.	M12E, A20 alternate.
	BP50	System Phones		M12E, A20		CS Series, 510 Syst.	Lift Handset
	BP8-111c	Analogue SLT's w/system		M12E, A20, SB2010		CS Series, 510 Syst.	
	BP250, MD110, MD Express	199, 202, 203, Console 2663		M22 with H-Top	S5T2	CS60: S1, TB, R2	M12E, A20 alternate. M12E/A20 to BPO Plug may be required on some phones.
		DBC212-01 System Phone		M12E, A20		CS Series, 510 Syst.	Contact installer for programming
		DBC755211 System Phone		M12E, A20			
	Cordless	DT292, DT590, DT430 ATEX, DT 412, DT422		----			No Headset Port
	Dialog 3000 Series	DBC 3201, 3202, 3203, 3210, 3211, 3212, 3213, Console 2663		M22 with H-Top	S5	Y: S1, TB, R3	
		ISDN 3310					
	Dialog 4000 Series	Analogue, 4106, 4147, 4186					
		Digital 4220, 4222, 4223, 4224, 4225		P-Top, or H-Top & P cable		Y: S1, TB, R3	Inbuilt Headset Port- P-Top quite loud.
		IP Series 4422, 4425		H-Top & P cable		Y: S1, TB, R3	Inbuilt Headset Port.
	FreeSet DECT	DS300		M-Top			
		DT310		M-Top			Requires FreeSet Headset Adaptor Module
		DT360		M-Top			Requires FreeSet Headset Adaptor Module
	MD110	Dialog 2500		E-10 & H-Top		Y: S1, TB, R3	
		Dialog 2600		M22 & H-Top		Y: S1, TB, R3	
		300 Series, Dialog 3200(D3), DNA, OPI 3000, Symbolic		M22 & H-Top		CS Series, 510 Syst.	
	Select			M22 & H-Top		CS Series, 510 Syst.	
	Temp 28i, 96i	Exec 22, Exec 34 Standard		M22 & H-Top		CS Series, 510 Syst.	
	IP Softphone	IP Softphone		DA40/55/60 & H-Top		CS60 / 510 USB	



Headset Solutions

Compatibility Guide - May 2007

Manufacturer	Equipment Type	Telephone/Console	Headset Key Prog.?	Corded Solution(s)	M22/12 Set-up*	Cordless Solution(s)	Comments
FUJITSU	F600 Series (ie 610, 620, 640)	represent Fujitsu terminal part number					
		Attendant Console <b>E08B-3139-S000</b>	Auto	HS0599-3S, or M22 with H-Top	S5,T2	CS Series, 510 Syst.	
		AT-I, AT-II, AT-III, AT-IV <b>F640-AT1, AT2, AT3, AT4</b>	User	HS0599-3S, or M22 with H-Top	S5,T2	CS Series, 510 Syst.	
	Coral 1,2,3, 630, 650		User	M12E, A20		CS Series, 510 Syst.	
	E600 Essence (E630, E650)	Attendant Console <b>E08B-3139-S000</b>	Auto	HS0599-3S, or M22 with H-Top	S5,T2	CS Series, 510 Syst.	
		Administrator Phone DTEL48D <b>F840-D1D</b>		M12 with H-Top			
		FDT 1 <b>F10B-0787-B003#IV</b>	User	M22 with H-Top		CS Series, 510 Syst.	
		FDT 2 - ????????	User	M22 with H-Top		CS Series, 510 Syst.	
		FDT 3 <b>F10B-0785-B003#IV</b>	User	M22 with H-Top		CS Series, 510 Syst.	
		FDT 4 <b>F10B-0784-B003#IV</b>	User	M22 with H-Top		CS Series, 510 Syst.	
	F9600 Series FORTRIX	Attendant Console	Auto	M22 with H-Top		CS Series, 510 Syst.	
		ATTCON - D6	Auto	M22 with H-Top		CS Series, 510 Syst.	
		<b>E08B-3157-S000</b>					
	(VS, MS, M, XL)	Attendant Console	Auto	M22 with H-Top		CS Series, 510 Syst.	
		ATTCON - D7		M22 with H-Top		CS Series, 510 Syst.	
		<b>F9600BAC/D7</b>					
		MLDT I <b>F10B-0736-B501</b>	User	HS0599-3S, or M22 with H-Top	S5,T2	CS Series, 510 Syst.	
		MLDT II <b>F10B-0737-B501</b>	User	HS0599-3S, or M22 with H-Top	S5,T2	CS Series, 510 Syst.	
		MLDT III <b>F10B-0738-B501</b>	User	HS0599-3S, or M22 with H-Top	S5,T2	CS Series, 510 Syst.	
		MLDT IV <b>F10B-0739-B501</b>	User	HS0599-3S, or M22 with H-Top	S5,T2	CS Series, 510 Syst.	
		DT12DS MLDT12 or MLDT X2 <b>F10B-0790-B101</b>	User	HS0599-3S, or M22 with H-Top	S5,T2	CS Series, 510 Syst.	
		DT24DS MLDT24 or MLDT X3 <b>F10B-0789-B101</b>	User	HS0599-3S, or M22 with H-Top	S5,T2	CS Series, 510 Syst.	
	CORAL	TA-2002 <b>57200902800</b>	Technician	M22 with H-Top		CS Series, 510 Syst.	
		TA-2002 BL <b>57200902700</b>	Technician	M22 with H-Top or P-Top	S5,T2	CS Series, 510 Syst.	Headset Key is Tech. Programmable from System Maintenance Console
		TA-2002H <b>57200902900</b>		M22 with H-Top		CS Series, 510 Syst.	
		TA-2002H BL <b>57200903000</b>	Technician	M22 with H-Top or P-Top		CS Series, 510 Syst.	from System Maintenance Console
		DST (Digital Std Tel.) <b>72440760100</b>	Technician	M22 with H-Top		CS Series, 510 Syst.	
		DKT 1110 <b>72440761700</b>	Technician	M22 with H-Top or P-Top	S5,T2	CS Series, 510 Syst.	Headset Key is Tech. Programmable from System Maintenance Console
		DKT 1110 BL <b>72440763500</b>	Technician	M22 with H-Top or P-Top	S5,T2	CS Series, 510 Syst.	Headset Key is Tech. Programmable from System Maintenance Console
		DKT 2320 <b>72440761200</b>	Technician	M22 with H-Top or P-Top	S5,T2	CS Series, 510 Syst.	Headset Key is Tech. Programmable from System Maintenance Console
		DKT 2320 BL <b>72440763100</b>	Technician	M22 with H-Top or P-Top	S5,T2	CS Series, 510 Syst.	Headset Key is Tech. Programmable from System Maintenance Console
		DKT 2321 <b>72440761300</b>	Technician	M22 with H-Top or P-Top	S5,T2	CS Series, 510 Syst.	Headset Key is Tech. Programmable from System Maintenance Console
		DKT 2321BL <b>72440764200</b>	Technician	M22 with H-Top or P-Top	S5,T2	CS Series, 510 Syst.	Headset Key is Tech. Programmable from System Maintenance Console
		DKT 2322 <b>72440762600</b>	Technician	M22 with H-Top or P-Top	S5,T2	CS Series, 510 Syst.	Headset Key is Tech. Programmable from System Maintenance Console



Manufacturer	Equipment Type	Telephone/Console	Headset Key Prog.?	Corded Solution(s)	M22/12 Set-up*	Cordless Solution(s)	Comments
Opus 512		DKT 2322 Bl <b>72440765100</b>	Technician	M22 with H-Top or P-Top	S5,T2	CS Series, 510 Syst.	Headset Key is Tech. Programmable from System Maintenance Console
		GKT 4320 <b>72440968000</b>	Technician	M22 with H-Top or P-Top	S5,T2	CS Series, 510 Syst.	Headset Key is Tech. Programmable from System Maintenance Console
		GKT 4320 Bl <b>72440968300</b>	Technician	M22 with H-Top or P-Top	S5,T2	CS Series, 510 Syst.	Headset Key is Tech. Programmable from System Maintenance Console
		Console/System Telephones	User	M12E, A20		CS Series, 510 Syst.	
GE	EXP9500			M-Top			
GLOBALTECH	Interphone			M22 & H-Top, or P-Top		CS Series, 510 Syst.	
GOLDSTAR		308/816		M12E, A20		CS Series, 510 Syst.	
HYBEX	Key System	Handsets	Yes	M22 with H-Top	S5T2	CS Series, 510 Syst.	Program:(SPKR)775
	DK321	Handsets		H-Top & Vista Cable		CS Series, 510 Syst.	Headset port on telephone
HYTEL		Pro	Yes	M22 with H-Top		CS Series, 510 Syst.	Program:(FUNCTION) 9 # enables, (FUNCTION) 9 * disables.
HYUNDAI		HX HKP-816	Yes	M22 with H-Top		CS Series, 510 Syst.	Program:## # (on) and ## # * (off) With handset on receiver.
		System Telephones		M12E, A20		CS Series, 510 Syst.	
INTERQUARTZ	Analogue Feature Phones	9826, 9835, 9836, 9837, 98372, IQ 50, 90, 250, 450, IQTEL 80, 300, 500, E2, E3.		M22 with H-top	S5,T2	CS Series, 510 Syst.	Handset volume down; use M12 volume control.
		IQTEL 300, 500, E2, E3 - Headset Modified		P-Top		CS Series, 510 Syst.	
	Enterprise Series,	Idea, IQ260, IQ350, IQ360, IQ550, IQ560E	Auto	H-Top & P-Cable, or P-Top		CS Series, 510 Syst.	V-P switch (M12-Polaris) to choose cord wiring. Adjust Gain control for appropriate transmit level.
	Gemini Series	IQ750 IQ331		H-Top & P-Cable, or P-Top H-Top & P-Cable		CS Series, 510 Syst.	
	Studio Series	IQ330, 333 20 / 25	Auto	H-Top & P-Cable, or P-Top M22 with H-top	S5,T2	CS Series, 510 Syst.	Handset volume down; use M12 volume control.
INTER-TEL	INT1000, 2000	Mobile Handsets		Mobile Handset			
IPFX	As per Cisco					CS Series, 510 Syst.	
KIRK	KIRK DECT	Z-3020		M series			Mobile Headset
		Z-3040		CHS142P-4AR1			CHS142P-4AR1
LEADER	Leaderphones	720D, 724D, 1020D		H-Top & Vista Cable		CS Series, 510 Syst.	No Headset port, requires switchbox as well
		726, 852, 1026, 1052HS		H-Top & Vista Cable		CS Series, 510 Syst.	Dedicated Headset Port & switch for cable selection.
		HP1, HP2		H-Top & Vista Cable		CS Series, 510 Syst.	No Headset port, requires switchbox as well
LG ARIA (Also ARIA)	LKD	LKD 2/8/30/Series LDK 100/300 Dect System		M22 with H-Top		CS Series, 510 Syst. C-65	No Headset port, requires switchbox as well C-65
	7000 Series	7004, 7008, 7016, 7024		P-Top & QD-2.5mm		L510 & LG Bluetooth module or CS series (S1, TB, R3)	Program: Earjack mode, not headset mode.
	System Telephones	16, 28, 34, 100, 148, 162, 186.		M22 with H-Top		CS Series, 510 Syst.	Program : [TRAN/PNG] 5 7 enables; [TRAN/PNG] 5 7 disables; [MON] is used to answer and release calls.
	System Telephones	20, 50, 300, 600		M22 with H-Top		CS Series, 510 Syst.	Program for headset button
	Select Keysets	34E		P-Top		CS Series, 510 Syst.	Program : [TRAN/PNG] 5 7 enables; [TRAN/PNG] 5 7 disables; [MON] is used to answer and release calls.
	GD36D Goldstar			M22 with H-Top		CS Series, 510 Syst.	
	LDP-700	VoIP series phones		2.5mm Ad. & H-Top			



Headset Solutions

Compatibility Guide - May 2007

Manufacturer	Equipment Type	Telephone/Console	Headset Key Prog.?	Corded Solution(s)	M22/12 Set-up*	Cordless Solution(s)	Comments
LG-NORTEL (Also ARIA)	7000 Series Digital	7004, 7008, 7016		M22 with H-Top		CS / 510 (S1, TB, R3)	
		7024, 7024 LD		M22 with H-Top		CS / 510 (S1, TB, R3)	Alt. P-Top & QD-2.5mm (or M175, MX510, Mot versions)
		7004N		M22 with H-Top		CS / 510 (S1, TB, R3)	Alternate - P-Top & QD-2.5mm. L510 if BT module fitted.
	7000 Series IP	7008, 7016, 7024LD		M22 with H-Top		CS / 510 (S1, TB, R3)	Alt. P-Top & QD-2.5mm (or M175, MX510, Mot versions)
		7004N		M22 with H-Top		CS / 510 (S1, TB, R3)	Alternate - P-Top & QD-2.5mm. L510 if BT module fitted.
	Softphone	VoIP softphones		DA40/55/60 & H-Top		CS60 / 510 USB	
LUCENT (refer Avaya)	Definity	System Telephones		Refer "AVAYA"			Refer "AVAYA"
	Cyber Gear Gold	Analogue SLT's used with System		M12E, A20, SB2010		CS Series, 510 Syst.	
	INdEX 100, 200, 400, 800	System Telephones		M12E, A20		CS Series, 510 Syst.	
		Consoles 6, 7, 700, 7000PC		M22 with H-Top or P10 with H-Top		CS Series, 510 Syst.	Termination: "K" Plug
MTEL	SX2000	Console and Handsets 400Series Telephones		M22 with H-Top M12E, A20	S5	CS Series, 510 Syst. CS Series, 510 Syst.	Extra Handset Cord
	16E / 24E	Superset 3 & 4		M22 with H-Top	S5	Y: S1, R3	
		Superset 4001, 4015, 4025, 4150.		M22 with H-Top	S5	CS60: S1, TB, R3	
	IP Phones	5201, 5207, 5215, 5220, 5240.		M22 & H-Top, or P-Top	S5	CS60: S1, TB, R2	
		5230, 5250		M22 & H-Top, or P-Top	S5	CS60: S1, TB, R2	Handset located in centre of base
		Consoles 6, 7, 700, 7000PC		M22 with H-Top or P10 with H-Top		CS60: S1, T, R3	Termination: "K" Plug
	Spectrum	System Telephones		M12E, A20		CS Series, 510 Syst.	
N.E.C.		AT3, AT3B, AT30, Dterm Cordless, Dterm Cordless Lite		M22 with H-top M-Top		CS Series, 510 Syst. N/A	
		Integrated Console		M22 with H-top		CS Series, 510 Syst.	Requires straight 2.5mm audio plug to RJ to connect.
	NEAX 2000 IPS, 2400 IPX	Console SN 611 (2400 SDS)		M22 with H-top	S5,T9	CS Series, 510 Syst.	Remove plate under unit by lifting lever on the right hand side. Slide plate forwards. Set the four position switch to "D" (Dynamic). Console volume down, use M22 volume.
	NEAX 2000 IPS, 2400 IPX	Console HA 630Z, Console SN 626		P10H with H-top	S5,T9	CS Series, 510 Syst.	
		Dterm I		H-Top & P cable		CS Series, 510 Syst.	
		Dterm IIB, Dterm III		M22 with H-top	S5,T10	CS Series, 510 Syst.	Handset volume down, use M22 volume
	NEAX 7400 ICS(110, 120, 140, 160, 180)	Dterm 6D, Dterm16D, Dterm V		M22 with H-top	S5,T10	CS Series, 510 Syst.	Console volume down, use M22 volume control
		Console HA 630 Z, Console SN 626, SN 708		M22 with H-top	S1,T2	CS Series, 510 Syst.	No Batteries req. Console volume down, use M22 volume.
		Console SN 694		M22 with H-top	S1,T2	CS Series, 510 Syst.	As above, termination Slimline K Plug.
	NEAX 7400 IMX	Dterm 8DC, 16DS, 16DD, 24DS		M22 with H-top, or P-Top & ADA-1	S5,T8	CS Series, 510 Syst.	P-Top requires the handset to be fitted with NEC ADA-1 headset adaptor.
		Console SN716, Dterm 75, DTP-8-1A, DTP-16D- 1A, DTP-32-1A		P-top		CS / 510 S1	
	Ranger AK	Handsets		M22 with H-top	S5,T10	CS Series, 510 Syst.	Handset volume down, use M22 volume cont.
	Ranger DK / NDK Ranger Pro	Handsets	Yes	M22 with H-top, or P-Top & ADA-1	S5,T9	CS Series, 510 Syst.	P-Top requires the handset to be fitted with NEC ADA-1 headset adaptor.
		DTU-8-1A (Pro Talk)	Technician	H-top on P-cord		CS Series, 510 Syst.	
		DTU-16D-1A (Pro Exec)	Technician	H-top on P-cord		CS Series, 510 Syst.	
	SP-30 Softphone	Softphone		CA40/55/60+ H-Top		USB- CS60 or 510	Electronic Hookswitch (V 2.10 Personacall Required)
		DTU-32D-1A (Pro Mstr)	Technician	H-top on P-cord		CS Series, 510 Syst.	
	Xen Alpha	DTU-8-1A(Pro Talk), DTU-16D-1A(Pro Exec), DTU-32D-1A(Pro Master), Xen Look Handset.		H-Top & P-Cable, or P-Top		CS Series, 510 Syst.	Use P-Top if volume is not loud enough
	Xen Axis, Master	Talk, Vision Handsets		M22 with H-Top		CS Series, 510 Syst.	
	Xen Series i	Basic, Classic, Essential, Premium, Professional		H-Top & P-Cable.		CS Series, 510 Syst.	



Headset  
Solutions

Compatibility Guide - May 2007

Manufacturer	Equipment Type	Telephone/Console	Headset Key Prog.?	Corded Solution(s)	M22/12 Set-up*	Cordless Solution(s)	Comments
<b>NITSUKO</b>	961, Envoy	TX, DX, 328		M22 with H-Top		CS Series, 510 Syst.	Program : [CLI] 8 3 4 [SPK] . [SPK] key used to answer and release calls.
<b>NORTEL (Inc. Extcom)</b>	Aria	2 Button, 8 Button, 30 Button, Director	Technician	M22 with H-Top	S5,T10	CS Series, 510 Syst.	Handset volume down; use M22 volume control.
	BCM	T7100, T7208, T7316		M22 & H-Top or P-Top	T 5	Y: S1, TC, R3	Volume may be low with P-Top
	Companion DECT Handsets	C3060, C4000, C 4040	Auto	M-Top	N/A	N/A	CHS142P-4AR1
	GDK, Elite	Enhanced, Executive, Director, Elite-Enhance, Aria-2, 8 & 30 Button		M22 with H-Top	S5, T10	CS Series, 510 Syst.	Handset volume down, use M22 volume. Program : [TRANS] 5 7 [HOLD/SAVE] Line button to answer.
	Goldstar	Key System Handset		M22 with H-Top	S5, T1	CS Series, 510 Syst.	
	GSX	GSX, GSX- E		M22 with H-Top	S5, T1	CS Series, 510 Syst.	#####
	IP Phones	i2002 Phase 1, & i2004Phase 1		M22 & H-Top or P-Top	T 5	Y: S1, TC, R3	Extension Arm P/N may 71483-01 needed for Lifter
		i2002 Phase 2, & i2004Phase 2		M22 & H-Top, or H-Top & P-Cable	T 5	Y: S1, TC, R3	Extension Arm P/N may 71483-01 needed for Lifter
		i2004 "POE"		M22 & H-Top, or H-Top & P-Cable	T 5	Y: S1, TC, R3	If "POE" notation is not labelled on the bottom of the telephone system H-Top & P-Cable for direct connect.
		1140E/1120E/1110E		P-Top		CS Series/510Syst	510 Hookswitch with BT inbuilt in 1140E, FW Rel Rel C22.
		IP Softphone 2050 (2050)		DA60 & H-Top		CS60 /510USB	
	Meridian	3901, 3902	Yes	M22 with H-Top	S5,T8	Y: S1, TB, R3	BiWay switch and P-Top as alternative
		3903, 3904, 3905		M22 & H-Top or P-Top	S5,T8	Y: S1, TB, R3	
		M1250 (Console)	Yes	M22 with H-Top	S5,T1	Y: S1, TB, R3	Termination K-Plug (Two prong plug)
		M2250 (Console)	"	"	"	"	Console volume down, use M22 volume control
		M1309 (ACD Handset)	Yes	M22 with H-Top	S5	Y: S1, TC, R3	Handset volume down; use M22 volume control.
		M2006, M2008, M2317	Yes	M22 with H-Top	S5,T8	Y: S1, TC, R3	BiWay switch and P-Top as alternative
		M2216 (ACD Handset)	Yes	M22 & H-Top or P-Top	S5,T8	Y: S1, TC, R3	Handset volume down; use M22 volume control
		M2616	Yes	M22 & H-Top	S5,T8	Y: S1, TC, R3	Handset volume down; use M22 volume control. Biway & P-Top alternative.
		M5216,5316,5317		M22 & H-Top or P-Top	S5	Y: S1, TC, R3	Leave handset off hook and use RLS key
		M6310		M22 & H-Top	S5	Y: S1, TB, R3	
		M6320		M22 & H-Top or P-Top	S5	Y: S1, TB, R3	
		M7100		M22 & H-Top	S5	Y: S1, T, R3	BiWay switch and P-Top as alternative
		M7207, 7310, 7316, 7324		M22 & H-Top or P-Top	S5	Y: S1, TB, R1	
	SL-1, 100 Digital			M22 & H-Top	S5,T1	CS Series, 510 Syst.	
<b>NRX BUSINESS TELEPHONES</b>							
		NRX-1, NRX-4, NRX-2 Hotel		M22 with H-Top		CS Series, 510 Syst.	
		NRX-2H, NRX-3, NRX-2 Carrier		H-Top & Vista Cable		CS Series, 510 Syst.	Old Handsets may use P Cable
		NRX-5					
	Keyphone System	Handset			S5,T2	CS Series, 510 Syst.	
	Cordless	Longreach	Std	M-Series			Mobile headset
<b>OKI</b>							
	Keyphones	Digital 308, 616, 1232, Keytouch DT3SE		M12E, A20		CS Series, 510 Syst.	Program for Headset Button
<b>OKICOM</b>							
	Keyphones	Okicom-G		M12E, A20		CS Series, 510 Syst.	Program for Headset Button
	Headset Keyphones	SR616, SR128		M12E, A20		CS Series, 510 Syst.	Program for Headset Button
<b>OMNI</b>							
	Aristel	15 or 25 Button Display		H-Top & Vista Cable	S5, T2	CS Series, 510 Syst.	Program Headset # 5 6 #
		Keyphone		M22 with H-Top	S5, T2	CS Series, 510 Syst.	
		T200		M12E with H-Top	S3, T2	CS Series, 510 Syst.	
		15 or 25 Button Display		H-Top & Vista Cable	S5, T2	CS Series, 510 Syst.	
		UF-15, UF Director, UF Executive, UF KT 10D, UF Standard		M22 & H-Top, or P-Top & Reverse P-Cable	S5,T2	CS Series, 510 Syst.	Program Headset # 5 6 #
	Cordless	Longreach	Std	M-Series			Mobile headset



Headset Solutions

Compatibility Guide - May 2007

Manufacturer	Equipment Type	Telephone/Console	Headset Key Prog.?	Corded Solution(s)	M22/12 Set-up*	Cordless Solution(s)	Comments	
PANASONIC	Cordless	KXTC904-B, -W, 905-B, -W, 933-B, 935-B, 1851AL, D700ALB, D715, D735, M944-B, KXTG200-B, 210-S, 2400, 2500ALB, 2501ALS, 2503ALF, 2550, 2570, 2581, 2583ALS, 2650ALN, M240B, KXT7990, KXTC155AL, 255AL.		M-Series			Mobile headset	
		KXT123210, 123220, 123230, 123235, 123250, 12321D, KXT7030, 7050A, 7250AL, KXT7450. KXT2220, 2221, 2255, 2260, 2310, 2315.		M22 with H-Top	S5	Y: S1, TC	Need to lift handset for some models	
	Analogue Handsets	KXT7220AL, 7230AL, 7235AL.		M22 with H-Top		Y: S1, TB	Program : press [PROGRAM] 9 9 9, press 1 for handset or 2 for headset, then press [STORE] and press [PROGRAM].	
		KXT7330		M22 with H-Top	S5		H-Top with P cable, direct connect option.	
		KXT7425, 7433, 7436, 7450		M22 & H-Top, or P-Top & Reverse Polaris Cable	S5	Y: S1, TB, R2		
	Digital Handsets	308, 616, 1232	KXT7531, 7533, 7536, 7550, 7565.		M22 & H-Top or P-Top	S5	Y: S1, TB, R3	
			KXT7433AL, 7436AL, 7625AL, 7630AL, 7633AL, 7636AL, 7730AL, 7750AL.		H-Top & QD-2.5mm, or M-22 & H-Top.	S5	Y: S1, TB, R3	
		System Telephones	KXT7230		M22 with H-Top	S5, T5	Y: S1, TB	
			KXT161630A Sitem Phone		M12E, A20		CS Series, 510 Syst.	Program for Headset use
			KX-TD 816, 1232		M12E, A20		CS Series, 510 Syst.	Program for Headset Button
System Telephones	KX-TD 500	Tech	M12E, A20		CS Series, 510 Syst.	Contact Installer		
PHILIPS	D1200	Console		P10 with H-Top				
		Handsets		M22 with H-Top		CS Series, 510 Syst.		
	30P IS Series SBX Range Sopho-S, and Sopho-K	Console, Handsets		M12E, A20		Y: S1, TB, R3		
		Console, Handsets		M12E, A20		Y: S1, TB, R3		
		Console, Handsets		M22 with H-Top		Y: S1, TB, R3		
		Console		M22 with H-Top or HSB Series		Y: S1, TB, R3	Termination: "D" plug	
		Handsets		M22 with H-Top		CS Series, 510 Syst.		
PINGTEL	Xpressa IP phone	SIP Phone		DA60 & H-Top		CS60 USB / 510USB	Ver 2.1 & above supports electronic hookswitch.	
PLANTRONICS	Practica	T100		H-Top & P-Cable, or Practica H100		CS Series, 510 Syst.		
POLARIS		NRX2H, NRX3		26716-01 Vista Cable		CS Series, 510 Syst.	Cannot use T100 & H142N Headsets	
POLYCOM	SoundPoint IP	300, 500, 600		M22 & H-Top or P-Top	S5	Y: S1, TB, R3	Polycom Lifter Arm P/N: 76141-01. M15D: A, T 3.5	
		Pro		H-Top & QD-2.5mm.				
REVO	Entry, Basic, Std.			H-Top & P-Cable, or P-Top		CS Series & 510S	V-P switch (Vista - P cable) to choose cord wiring. Adjust Gain control for appropriate transmit level. HI-10 difficult to fit.	
ROCKWELL	Transend	SpectraView 1, 2 and SpectraSet Convergence	Yes	E10 and H-Top or M22 and H-Top SMH2130-01 with H-Top	S1	Y: S1, TD, R3	E10 preferred as it allows RNA feature to operate M22 - No Batteries Required	
							Multimedia amplifier to allow connection to soundcard and customers handsets	

Manufacturer	Equipment Type	Telephone/Console	Headset Key Prog.?	Corded Solution(s)	M22/12 Set-up*	Cordless Solution(s)	Comments
SAMSUNG	DCS, DCS 70, & DCS Compact	SLT-E, Economy Digital	No	H-Top & P Cable (recommended), or P Top, or M22 & H Top	S5,T2		If P-Top is too loud use H-Top & Polaris Cable (Biway switch if need to keep handset use).
		6B BBASIC, STD12B, STD24B, LCD24B, LCD24B.	User	H-Top & P Cable (recommended), or P Top, or M22 & H Top	S5,T2		Program : press [TRSF] 1 1 0, then press 2 0 for handset or 2 1 for headset, then press [TRSF] to store. [ANS/RLS] light will be on to indicate headset is active. Use [ANS/RLS] button.
		DECT Handsets (SPR5000)		----			Not Compatible
	DECT	8000		CHS142N-4AR1H/A			
	HX	Standard Keystation (No Display), Executive Keystation (LCD Display)	User	M12 with H-Top	S5,T2	CS Series / 510S	Handset volume down; use M12 volume Program: # 1 5 1 #
	Facsimile Machines	SF150, 110T, 1600, 2900M, 4000, 4100, 4120, 5500, 5600, 6050.	No	M12 with H-Top			
	Digital Handsets	Director(T2 Button), Navigator(21 Button), Navigator(14 Button), 64 Button Operator Console, Office(38 Button), Office(14 Button)Office (7 Button), Basic Digital.		H-Top & P Cable (recommended), or P Top, or M22 & H Top		CS Series / 510S	If P-Top is too loud use H-Top & P- Cable (Biway switch if need to keep handset use)
	IP Handsets	Director(T2 Button), Navigator(21 Button), Navigator(14 Button).	No	H-Top & P Cable (recommended), or P Top, or H12 & H Top		CS Series / 510S	If P-Top is too loud use H-Top & P-Cable (Biway switch if need to keep handset use)
	DX Series	5007, 5012L, 5014-5021D, 5038		H-Top & P Cable (recommended), or P Top, or M22 & H Top		CS Series / 510S	If P-Top is too loud use H-Top & P-Cable (Biway switch if need to keep handset use)
		ITP-5012L, 5014& 021D		M22 with H-Top		CS Series / 510S	
SIEMENS	2-Wire Telephones	Profiset 10, 30, Set 211, 221		M22 with H-Top	S5,T9	CS Series / 510S	Handset volume down; use M12 volume
	CDSS System	Console		M22 with H-Top	S1, T2	CS Series / 510S	Termination: J Plug; Handset volume down; use M12 volume
	DX20	Console		M22 with H-Top	S5,T2	CS Series / 510S	
	EMS Attendant Consoles	30, 80					Not Compatible (Hardwired)
		60, 150, 12000		M22 with H-Top	S5,T2	CS Series / 510S	Termination: M Plug (wiring varies)
		601		M22 with H-Top	S5,T2	CS Series / 510S	Termination: Slimline K Plug
	Hicom 100	T8, T16D	Tech.	M22 with H-Top	S5,T9	CS60: S1, TB, R2	
		T16		M22 & H-Top, or P-Top		CS60: S1, TB, R2	
	Hicom 110/120/130	Ultrasat Standard, Ultrasat Comfort	Tech.	M22 with H-Top	S5,T9	CS Series / 510S	
		Ultrasat Memory	Tech.	M22 with H-Top	S5,T2	CS Series / 510S	
		Optiset E Advance, Advance Plus, Basic, Entry, Memory, Standard	Tech.	M22 & H-Top, or P-Top	S5,T2	CS Series / 510S	Plug into Headset Socket
		Optiset, PC Based	Tech.	M22 with H-Top	S5,T2	CS Series / 510S	Requires Siemens adaptor set AC2
	Hicom 118E, 118-2E, 150E	System Telephones	Yes	M12E, A20		CS Series / 510S	
	ISDX System	Console MKI, MKIII, IIIA, IV, Screen Based		M22 with H-Top	S1, T3	CS60: S1, TB, R2	Occasionally requires U-Plug (Right Hand Pin)
		Agent Set, ISDT, ISDT300, QLINK		M22 & H-Top, or P-Top	S5,T8	CS60: S1, TB, R3	
		ISDT300+		-----			Not Compatible (Hardwired)
		Multiline ML16S, M3000, M5000		M22 with H-Top	S5,T2	CS Series / 510S	Termination: U Plug (Left Hand Pin); Handset Volume down, use M12 volume
		M8, M8+, M1200, M2000		-----			Not Compatible (Hardwired)
	HiPath 500, 3000, 4000, 5000	OptiPoint 400, 500, (Entry, Economy, Standard, Advance)	Tech.	M22 & H-Top, or P-Top	S5,T2	CS60: S1, TB, R3	Entry-M12 & Amp Only; Economy - M12 & Amp or Siemens Acoustic Adapter with H-Top & P cable; Std & Adv - Direct Connect P-Top
		OptiPoint 600 Office	Tech.	M22 & H-Top, or P-Top	S5,T2	CS60: S1, TB, R3	Plug into Headset Socket
Com, Office Pro, Point	System Telephones	Yes	M12E, A20		CS Series / 510S		
Gigasets	SL100/S440		MX153-SM2 Mobile		C65		
	C100/200/250/340		N/A		C65		
SoftPhone	optiClient130		DA60 & H-Top		CS60 USB/510 USB		



Headset Solutions

Compatibility Guide - May 2007

Manufacturer	Equipment Type	Telephone/Console	Headset Key Prog.?	Corded Solution(s)	M22/12 Set-up*	Cordless Solution(s)	Comments
SKYPE	Softphone	Skype V1.0 or later		DA60 & H-Top		CS60 USB/510USB	Full Hookswitch Control Skype V1.0 and above
SOLOMON	Mini PBX System	SPX208		M12E, A20, SB2010		CS Series / 510S	
SONY	SPP-M932	Cordless		M series			Mobile Headset
SOXCOM		Tennyson Handset		H-Top with P cable		CS Series / 510S	Mobile Headset
SPECTRALINK	Wireless IP	e340, i640		2.5 mm to QD, & H-Top		N/A	Some earlier handsets require 3.5 mm to QD.
	Wireless IP	Docking Station		M-22 & H-Top		N/A	
TELSTRA (inc. PlesTel)	Commander AN 616	All Handsets	Yes Kit Required	M22 with H-Top	S5,T2	CS Series / 510S	Handset volume down; use M22 volume control
	Commander BN (512, 824, 1236, 2464)	All Handsets	Yes Kit Required	M22 with H-Top	S5,T2	CS Series / 510S	Handset volume down; use M22 volume control
	Commander D	All System Integral Handsets	Yes	M12E with H-Top or H-Top on H-Cord	S3,T2	CS Series / 510S	H'Set Key Prog: [SPKR] 6 2 6 [SPKR] Note: H-Top on cord performance is borderline
	Commander E	All Handsets	No	M12E with H-Top or H-Top on H-Cord	S3,T2	CS Series / 510S	Note: H-Top on cord performance is borderline
	Commander HX (308, 616, 2464)	Standard Keystation (No Display)	User	M22 with H-Top	S5,T2	CS Series / 510S	Handset volume down; use M22 volume control H'Set Key Prog: # 15 1 #
		Executive Keystation (LCD Display)	User	M22 with H-Top	S5,T2	CS Series / 510S	Handset volume down; use M22 volume control H'Set Key Prog: # 15 1 #
	Commander I	All Handsets	Yes	M22 with H-Top		CS Series / 510S	
	Commander N	All Handsets	N/A	Not Compatible		N/A	Handsets are hardwired
	Commander NT (NT40, NT132)	Economy	No	P-Top M22 with H-Top	S5,T2	CS Series / 510S	No headset port; replace handset with P-Top
		Standard	Yes	P-Top M12 with H-Top	S5,T2	CS Series / 510S	Dedicated headset port. Prog. for Full-Handsfree to get Headset Key
		Advantage	Yes	P-Top M22 with H-Top	S5,T2	CS Series / 510S	Dedicated headset port. Prog. for Full-Handsfree to get Headset Key
		Principle	Yes	P-Top M22 with H-Top	S5,T2	CS Series / 510S	Dedicated headset port. Prog. for Full-Handsfree to get Headset Key
	Commander S	S206, S408, S824	?	M22 with H-Top	S5,T2	CS Series / 510S	Handset volume down; use M22 volume control
		S207, S416, S620	N/A	Not Compatible	N/A	N/A	Handsets are hardwired
	Commander T	T105	N/A	Not Compatible	N/A	N/A	Handsets are hardwired
		T106, T210	Yes Kit Required	M22 with H-Top	S1,T2	CS Series / 510S	Handset volume down; use M22 volume control
	Connect			H-Top with P cable		CS Series / 510S	
	E-PABX		Yes	M22 with H-Top	S5,T2	CS Series / 510S	
	E-PATH						
	Retail Phones	A228, A248, Access 25, Access 35.		M22 with H-Top	S5,T2	CS Series / 510S	
		Freedom 500	Yes	H-top on 40845-01			40845-01 plugs into 3.5mm socket on handset
		T1000C, T1000S		H-Top & Vista Cable		CS Series, 510 S	
	Spectrum	B1450 (578/102)		H-Top & Vista Cable		CS Series / 510S	Dedicated headset port.
	T1000C	T100F, 1000F, 1000C		H-Top & M15D, or Vista Cable		CS Series, or 510S	BiWay with H-Top & Vista Cable an option. Kit required, if M-22 used.
	T1000S (Thomson) Terminals	M5317 (578/107)		M22 & H-Top, or P-Top	S5,T2	CS Series / 510S	BiWay with H-Top & Vista Cable an option.
		M5316 (578/19), P-Phone Prof.		M22 & H-Top, or P-Top		CS Series / 510S	
		M5216 (578/20), P-Phone ACD		P-Top		CS Series / 510S	Dedicated headset port.
		M6320		P-Top		CS Series / 510S	Dedicated headset port.
	Touchfone	200, 300, 400, Executive	No	M22 & H-Top, or H-Top & Vista Cable	S3,T2	CS Series / 510S	Note: H-Top on cord performance is borderline
	Vision		Yes	M22 & H-Top, or H-Top & P Cable	S5,T2	CS Series / 510S	For S12 settings use S2T2
TOSHIBA		DK40		M22 with H-Top	S5	Y: S1, TD, R2	



Solutions

Compatibility Guide - May 2007

Manufacturer	Equipment Type	Telephone/Console	Headset Key Prog.?	Corded Solution(s)	M22/12 Set-up*	Cordless Solution(s)	Comments
UNIDEN		ANA900, EXP95, 95i, 97, 900, 9110, 9500, EXS9600, 9800, MER9500, NOR9500		M series		N/A	Mobile Headset
VTECH		900NDL, 910 ADL, 917ADX, 922CID, 1980, 9000		M series		N/A	Mobile Headset
<b>WAVELINK COMMUNICATIONS (Refer KIRK)</b>							
YAHOO	SoftPhone	SIP Phone		DA60 & H-Top		CS60 USB / 510 USB	
ZULTYS	ZIP 2			M22 & H-Top		CS Series, or 510S	No Headset connection, cannot connect.
	ZIP 11			H-Top & QD-2.5mm		CS Series, or 510S	
	ZIP 4 x 4			H-Top & QD-2.5mm		Y: S1, TB, R3	
	ZIP 4 x 5			H-Top & QD-2.5mm		CS Series, Bluetooth	Inbuilt BT module with 510 Hookswitch Control.

